



Sample image

KG105

Type Size: S1

Classification Contact: Rigid contact bridge

Classification Contact Mat: Silver

Classification Terminal: Screw terminal

IEC 60947-3 EN 60947-3, VDE 0660 Teil 107

Rated insulation voltage Ui

Voltage (V)	AC / DC
690	AC

Rated impulse withstand voltage Uimp

Voltage (kV)	Overvoltage category	Pollution degree	Supply system	Function
6	III	3	Valid for lines with grounded common neutral termination	Switch / Switch disconnecter

Rated uninterrupted current Iu/Ith

Current (A)	Ambient temperature (°C)	Peak temperature (°C)	additional requirements
125	50	55	Ambient temperature +50°C during 24 hours with peaks up to +55°C

Conventional enclosed thermal current Ithe

Current (A)	Ambient temperature (°C)	Peak temperature (°C)	Additional requirements	No. of stages (from - to)	Mounting	Mounting size
125	35	40	Ambient temperature +35°C during 24 hours with peaks up to +40°C	--	--	--

Rated operational current Ie

Utilization category	Voltage (V)	Current (A)
AC-32A	20 - 400	125
AC-20A	690	125
AC-21A	20 - 690	125
AC-22A	220 - 500	125
AC-22A	660 - 690	90

Rated operational power

Utilization category	Voltage (V)	No. of phases	No. of poles	Power (kW)
AC-3	220 - 240	3	3	22
AC-3	380 - 440	3	3	37
AC-3	500 - 500	3	3	45
AC-3	660 - 690	3	3	22
AC-23A	220 - 240	3	3	25
AC-23A	380 - 440	3	3	45
AC-23A	500 - 500	3	3	55
AC-23A	660 - 690	3	3	30

Max Fuse Rating IEC

Fuse characteristic	No. of Fuses	Current (A)
gG	1	125

UL60947-4-1, UL508

Rated insulation voltage Ui

Voltage (V)	AC / DC
600	AC

Rated thermal current

Current (A)	Ambient temperature (°C)	Additional Text
125	0 - 40	ON-OFF switch (Valid when connected with wire rated for 75°C)
115	0 - 40	Change over switch (Valid when connected with wire rated for 75°C)

General Information
Text

- The operating handle and position indicating means to be used with these manual motor controllers should be provided from the manufacturer, or the operating handle and position indicating means to be used should have been previously evaluated in combination with the manual motor controllers.

General Information
Text

- When intended for use as a motor disconnecter the device shall be provided with a method of being locked in the OFF-position.

GENERAL TECHNICAL INFORMATION
Tightening torque of screws

<i>tightening torque (Nm)</i>	<i>tightening torque (lb-in)</i>
3	27

Rated short-time withstand current Icw

<i>Time (s)</i>	<i>Current (A)</i>
1	2000

Size of conductor

<i>composition of conductor</i>	<i>Min. / Max. value</i>	<i>No. of conductor per terminal</i>	<i>Cross section (mm²) or (AWG/kcmil)</i>	<i>Material of the wire</i>
solid wire	Min.	1	2.5mm ²	Copper
flexible wire	Min.	1	4mm ²	Copper
flexible wire	Max.	1	35mm ²	Copper
flexible wire	Max.	1	AWG 2	Copper
Single-core or stranded wire	Max.	1	AWG 1/0	Copper
Single-core or stranded wire	Max.	1	50mm ²	Copper
flexible wire with sleeve	Max.	1	35mm ²	Copper
flexible wire with ferrule according to DIN 46228	Min.	1	2.5mm ²	Copper

Approbations
Specification
Marking

EAC



CE marking



UK Directives

IEC 60947-3; EN 60947-3; VDE 0660 Teil107

IEC 60947-3
EN 60947-3

IEC 60947-6-1

IEC 60947-6-1
EN 60947-6-1

UL 60947-4-1; CSA C22.2 No. 60947-4-1



GB/T14048.3



Russian Maritime Register of Shipping


Power loss per pole

Power (W)

3,80

Conditions during transport and storing

<i>Minimum temperature (°C)</i>	<i>Maximum temperature (°C)</i>	<i>additional requirements</i>
-40	85	In case of temperatures below -5°C no shock load permissible

Shock / Vibration
Type of oscillation
Values

Resistance to vibration

Min. 4g, 2-100Hz, 1,6mm

Resistance to shock

min. 6g, 6ms

General Information
Text

- EMC Note: This device is suitable for use in environment A and B.

- Do not lubricate or treat contacts.

- Switches may only be mounted, connected and set into operation by qualified persons according to the accepted rules of technology.

- Use copper wire only. Do not coat the wire end with tin.

- Terminals with factory fitted jumper links are tightened during production. Take care during installation to ensure factory fitted links are not lost by undoing both sides of linked terminals. After wiring, all terminal screws must be tightened to recommended torque specifications.

Operating temperature

<i>Min. Temperature [°C]</i>	<i>Max. Temperature [°C]</i>
-5	55